



SECURINESS

MantaRay

 Kontakt os venligst for mere information

Close Range Phone Detector

HANDHELD MODE RANGE	0 - 15 cm
STATIONARY MODE RANGE	0 - 30 cm
CALIBRATION seconds (only applies to stationary mode)	Approximately 3
WARM UP	Approximately 15 minutes (only applies to stationary mode)
POSSIBLE FALSE TRIGGERS	Some metallic objects, surfaces & areas of high ferromagnetic activity
WEIGHT	283 gram
DIMENSIONS	17.8 x 7.6 x 5 cm
ALERTS	LCD, audio & blinking LEDs
CONTROLS	Trigger for power ON/OFF
SCREEN	Color TFT LCD 160 x 128 resolution
POWER MH,	Removable 9 volt battery (alkaline & rechargeable Ni-lithium-ion batteries supported) 12 VDC 1A AC Adapter (included) (consumes < 0.1A @ 12V)
RUNTIME	Up to 3 hours of continuous use on standard 9V alkaline battery
INCLUDES	(2) 9 Volt alkaline batteries, hand strap, SD memory card containing videos & user guide AC power adapter (for stationary mode)



SECURINESS MantaRay

Kontakt os venligst for pris

Alle priser er eksklusive moms, levering og installation